

# UPS2000-A Series

## (6-10kVA)

### Introduction

---

UPS2000-A series (6-10kVA) is a tower-mounted, online double conversion power system that delivers continuous, high-quality AC Power. up to 96% efficiency at online mode for 6/10kVA models helps save 50% energy cost. It's really a perfect power protection solution for small power scenarios.

### Scenarios

---

- Small and medium enterprises, large enterprise branch offices, bank branches and other small data centers
- Networks, communications systems, automatic control systems and other precision equipment
- Family, office

### Features

---

#### Reliable

- Wide input voltage range to minimize battery use
- Key component failure pre-alarm including fans, batteries to remind customers to maintain before failure occurs
- Coating design & key device pin special protection enhance reliability

#### Efficient

- High efficiency of up to 96% at online mode for 6/10kVA reduces power loss of UPS and air conditioner and saves customers more than 50% over less efficient models
- The output power factor is 0.9, high load capacity

#### Simple

- LCD screen supports real-time monitoring and convenient operation
- Built-in battery design provides you integrated solution and makes it especially applicable for space-scarce use
- 6kVA/10kVA Professional Edition supports 4 machines in parallel operation, built in maintenance bypass, easy to use
- The NetEco 1000U management system monitors UPSs in real time and allows users easy management, and operation
- Multiple remote monitoring: supports SMS, E-mail, etc



UPS2000-A-6K/10K

# Specifications

Rated capacity (kVA/kW)			6kVA/5.4kW (Standard Version)	10kVA/9kW (Standard Version)	6kVA/5.4kW (Professional version)	10kVA/9kW (Professional Version)
Model			UPS2000-A-6KTTL-S UPS2000-A-6KTTS-S		UPS2000-A-6KTTL-P UPS2000-A-6KTTS-P	
Input: Output			1 phase input, 1 phase output			1 phase input, 1 phase output; dual-live-wire input, dual-live-wire output
Mains	Input Wiring		L+N+PE			L+N+PE/2Ph+PE
	Rated Input Voltage		220/230/240 V AC			208/220/230/240 V AC
	Input Voltage Range		80-280 V AC			
	Input Frequency Range		50/60 Hz $\pm$ 5 Hz			
	Input power factor		$\geq$ 0.99			
	Total Harmonic Distortion		Total Harmonic Distortion of current <3% at rated load			
Bypass Input	Input rated voltage		220/230/240 V AC			208/220/230/240 V AC
	Input frequency range		50/60 Hz $\pm$ 5 Hz			
Battery	Battery voltage	Standard	192 V DC	192 V DC	240 V DC	240 V DC
		Long backup	192-240 V DC	192-240 V DC	192-240 VDC	192-240 V DC
	Backup time	Standard	> 5 minutes at 80% rated load	> 4 minutes at 80% rated load	> 6 minutes at 80% rated load	> 5 minutes at 80% rated load
		Long backup	Depending on the capacity of external batteries			
Output	Output wiring		L+N+PE			L+N+PE/2Ph+PE
	Rated voltage		220/230/240 V AC $\pm$ 1%			208/220/230/240 V AC $\pm$ 1%
	Output frequency		Tracking the bypass input (Online Mode); 50/60 Hz $\pm$ 0.05 Hz (Battery Mode)			
	Output power factor		0.9			
	Waveform		Sine wave, THDv $\leq$ 2%			
System	Maintenance Bypass		No Built-in Maintenance Bypass			Built-in Maintenance Bypass
	Expandability		----			Up to 4 units connected in parallel
	Efficiency		96%			
	Overload capacity		125% overload for 5 minutes; 150% overload for 1 minute			
Environment	Operating Temperature		0°C to 40°C			
	Relative Humidity		0%–95% RH (no condensation)			
	Altitude		0-1000m. Above 1,000 m, derating 1% for each additional 100 m			
	Audible Noise		<50dB @ 1 Meter			
Others	Height x Width x Depth		580 mm x 250 mm x 605 mm			
	Weight	Standard	60 kg	67 kg	70 kg	79 kg
		Long backup	20 kg	21 kg	21 kg	22 kg
	Certifications		EN/IEC62040-1, EN/IEC62040-2, EN/IEC62040-3, CE, CB, RoHS, REACH, WEEE, RCM, etc.			
	Communications		USB(optional RS485/Dry contact/SNMP)			

## General Disclaimer

The information in this document may contain predictive statements including, without limitation, statements regarding the future financial and operating results, future product portfolio, new technology, etc. There are a number of factors that could cause actual results and developments to differ materially from those expressed or implied in the predictive statements. Therefore, such information is provided for reference purpose only and constitutes neither an offer nor an acceptance. Huawei may change the information at any time without notice.

## HUAWEI TECHNOLOGIES CO., LTD.

Huawei Industrial Base  
Bantian Longgang  
Shenzhen 518129, P.R. China  
Tel: +86-755-28780808  
Version No.: M3-022333-20150423-C-3.0  
[www.huawei.com](http://www.huawei.com)